
DS-K2702X - Controladora Hikvision con caja. Admite control de 2 puertas



SKU: DS-K2702X

Link: <https://www.mundicam.com/productos/control-accesos/controles-acceso/controladoras/ds-k2702x/>

PRODUCT INFORMATION

Marcas: 2344

Categorías: ACCESOS, Controladoras

Etiquetas: HIKVISION

Admite control de 2 puertas. Puede ampliarse hasta 62 módulos de acceso DS-K2M002X y se pueden controlar hasta 126 puertas. Diseño de cableado redundante RS-485 de enlace descendente para garantizar la estabilidad de la comunicación. La interfaz RS-485 de enlace descendente de 5 canales admite dos aplicaciones: 1. Cuando se utiliza una comunicación RS-485 de 4 canales, el quinto RS-485 se puede utilizar como una aplicación redundante; 2. El RS-485 de 4 canales forma 2 grupos de bucles de bus dual con aislamiento físico. Se recomienda que no tenga más de 16 módulos de acceso conectados a cada bus de bucle. Gestión de configuración web. Todas las configuraciones se pueden realizar a través de la web sin necesidad de una aplicación de software. Admite aplicaciones de control de acceso profesional, como enclavamiento de múltiples puertas y anti-passback. Admite acceso a batería de respaldo. Se pueden cargar y descargar. Tiene indicadores de estado como suministro de energía, comunicación y operación, lo que es conveniente para la detección del estado del equipo.

ESPECIFICACIONES TÉCNICAS

Sistema

Sistema operativo Linux

Red

Red cableada 1, 10/100/1000 Mbps self-adaptive

Interfaz

Interfaz de red 1

Lock control 2

Botón de salida 2

Entrada de contacto de puerta 2

Entrada de alarma 4

Salida de alarma 4

Tamper 1

RS-4857, 2 for card reader, 5 for access modules (4 for communication, each interface can connect up to 16 access modules; 1 for redundancy)

Wiegand 4, standard 26/34 input, supports custom Wiegand settings

USB 1, USB 2.0

Fire interface1

Capacidad

User capacity 100,000

Capacidad de huella digital 10,000

Capacidad de tarjetas 200,000

Capacidad de eventos 600,000

Linked door capacity Self: 2 doors Extended: up to 126 doors (connected with 62 access modules)

Linked card reader capacity 4 RS-485 card readers (OSDP protocol) and 4 Wiegand card readers

Autenticación

General

indicador 10 indicators, 1 for indicating power status, 1 for running status, 1 for wired network status, 5 for RS-485 status, and 2 for door status

Fuente de alimentación 100 VAC to 240 VAC

batería Charge and discharge

Consumo de energía ? 72 W

Temperatura de trabajo -10 °C to 55 °C (14 °F to 131 ° F)

Humedad de trabajo 0% to 90% (No condensing)

Instalación Wall mounting

Idioma English, Thai, Traditional Chinese, Indonesian, Vietnamese, Arabic, Spanish (Europe), Spanish (South America), Italian, French, Dutch, Russian, Ukrainian, Portuguese (Europe), Portuguese (Brazil), Serbian, Croatian, Bulgarian, German, Greek, Romanian

Función

Configuration via Web browser Support

Autenticación multifactor Support

Entrada de primera persona Support

Anti-passback Support 32 routes (64 card readers each)

Multi-door interlocking Support 32 groups (32 doors each)